# moooi

# NR2 Floor Lamp BERTJAN POT

See the world from your own elegant and lighthearted bubble: the NR2 Floorlamp doesn't block the view. This new creation by Bertjan Pot is a symmetric LED treasure that gracefully balances on a steel frame.

Detailing



Colours

The NR2 features a branded light diffuser that seamlessly integrates the metal frame.

Black

White

NR2 Floor Lamp Medium

#### Dimensions

56cm | 22"



#### Product

**width** 56cm | 22" неіднт 164ст | 64.6" **дертн** 56cm | 22" **DIAMETER** 56cm | 22"  $\textbf{weight netto}~4.5kg~|~9.92lbs \quad \textbf{weight}~10.5cm~|~23.15lbs$ 

#### Packaging

**width** 69.5cm | 27.4" **ныднт** 172.1cm | 67.8" **CUBAGE** 0.78m<sup>3</sup> | 27.67ft<sup>3</sup> LENGTH 65.5cm | 25.8"

### Technical CE

#### MATERIAL

Ellipsoid from fiberglass with epoxy resin, ABS cover, PC diffuser and aluminum heatsink on a powdercoated steel stand

<b>ENERGY LABEL</b> Energy Label B	<b>LIGHTSOURCE TYPE</b> LED
NUMBER OF LIGHTSOURCES	DIAMETER SHADE
1	56cm 22"
INPUT VOLTAGE	FREQUENCY
208-277	50/60
MAX POWER CONSUMPTION	DIMMABLE
16W	Yes
LAMPHOLDER	COLOUR
LED (Solid state)	Black
PLUG TYPE	CABLE LENGTH
Europlug (Type-C)	350cm   137.8"
SWITCH	COLOUR TEMPERATUE
In line slide dimmer with on/off switch	2700 K
CRI	LIGHT DIRECTION
82	All directions
LIGHT OUTPUT	
450 lm	

Technical cULus

#### MATERIAL

Ellipsoid from fiberglass with epoxy resin, ABS cover, PC diffuser and aluminum heatsink on a powdercoated steel stand

ENERGY LABEL	LIGHTSOURCE TYPE
Energy Label B	LED
NUMBER OF LIGHTSOURCES	DIAMETER SHADE
1	56cm   22"
	FREQUENCY
120	50/60
MAX POWER CONSUMPTION	DIMMABLE
16W	Yes
LAMPHOLDER	COLOUR
LED (Solid state)	Black
PLUG TYPE	CABLE LENGTH
US plug (Type A)	350cm   137.8"
OS piùg (Type A)	550000000
SWITCH	COLOUR TEMPERATUE
In line slide dimmer with on/off switch	2700 K
CRI	
82	All directions

**LIGHT OUTPUT** 450 lm

## Dimmer

For fluent dimming behaviour we advise a dimmer that is	DIMMER TYPE
compatible with the following specs.	Dimmer on

Please note the functioning of the dimmer and the power supply combination can never be predicted, it always needs to be tested in practice.

DIMMER TYPE Dimmer on power cord